
Mitel 5614 Quick Reference Card



Display Icons

ill Signal Strength

- 💁 Voice Mail
- Microphone Off/Muted
- Loudspeaker On
- Loudspeaker Off
- Sound Off
- Headset Connected
- 🖂 New Message
- New Message, Important
- R Bluetooth Headset

- Multifunction/Alarm Button
 Earpiece Speaker
- 3 Volume Up
- 4 Volume Down
- 5 Mute and PTT Button
- 6 Softkeys
- 7 Off-Hook Key
- 8 Five-way Navigation Key
- 9 Voice Mail Access
- 10 Key Lock and Upper/Lower Case
- 11 Microphone
- 12 Space

戻 Read Message

Missed Call

□ Incoming Call

□ → Outgoing Call

Key Lock

*

Phone Lock

Bluetooth

Profile Active

System Connection

New Colored Message

- 13 Sound Off key
- 14 Tactile Indicators
- 15 End and On/Off key
- 16 Color Display
- 17 Headset Connector

Turning the Handset On/Off

- Press and hold the **On-hook** key suntil "Switch on/off is displayed.
- 2. Press "Yes/No."

Making a Call

Dial the number and press
C. The name of the called party is displayed if available.
OR

Press roopen the call list and use the Navigation key to scroll the list of your last twenty calls. Press root dial.

OR

- 1. Press the Menu softkey.
- 2. Select Contacts, and select Call contact.
- 3. Select contact from list.
- 4. Press *r* or Call to dial the number.

Answering a Call

- Press the Handsfree key to answer in speaker mode.

Ending a Call

Press S to end a call.

Placing a call on Hold

- 1. Press the More softkey.
- 2. Select Hold/Retrieve to put the call on hold.

To retrieve the Held call:

- 1. Press the More softkey.
- 2. Select Hold/Retrieve to retrieve the call on hold.

Transferring a Call

- 1. Press the More softkey.
- 2. Select Transfer to New Call.
- 3. Dial the number to which you want to transfer the call and press Call.
- 4. Select Release to connect the two parties.

OR

Wait for an answer, announce the transfer and then select Release.

Conference

- 1. Press the More softkey.
- 2. Select New Call to put the current call on hold.
- 3. Dial the number of the third party.
- 4. Wait for an answer.
- 5. Press More and then select Conference Call to conference all the parties together.

Rejecting a Call

• When the ring signal sounds, press S Call information will be stored in the Call list.

Adjusting Volume Levels

To adjust earpiece volume during a call:

 Press upper and lower volume buttons to increase/decrease volume.

To change ringer volume:

- In the menu, select Settings.
- Select Sound & Alerts.
- Select Volume.
- Use the navigation key arrows to adjust selected volume and press Back to save.

To turn Loudspeaker on/off:

 Press the Handsfree key defore or during a call.



To turn ring signal on/off in standby mode:

Press #) to toggle ring signal on/off. (The silenced icon variable appears.)

Locking/Unlocking the keypad:

- Press # and then Lock to lock.
- Select # and then Yes to unlock.

Charging the Battery

Place the handset in the desktop charger. The Battery icon indicates charge level. The phone is fully functional while in the charger.

Navigating the Menu

Enter the menu by pressing the Menu key. Use the Left/Right navigation keys to choose a tab, and then press the middle round (Confirmation) button on the navigation key or the Select softkey to open it. Use the Up/Down navigation keys to scroll through menu choices. Press the middle Confirmation button to make a selection or press Back to back up one step. Confirm your settings by pressing the

Confirmation button. Return to standby mode by pressing Back or the 🌋 key.

On-hook/Standby Menu



Connections 🥑	Bluetooth Headset		Sound & Alerts
	System		Locks
	In Charger	Settings 🔅	Display
Calls 🕻	Call List		Time & Date
	Missed Calls		Answering
	Call Time		Messages
	Push to Talk (PTT) Options		Language
	Call Services		Owner ID
Shortcuts ⊘	Softkeys	Profiles 🔊	Add New Profile
	Hot keys		Activate Profile
	Navigation keys		Delete Profile
	Multifunction button		Edit Profile
Services 💌	Add	Contacts	Call Contact
	Edit		Add Contact
	Delete		Edit Contact
Messaging 🖂	Inbox		Set Ring Signal for a Contact
	Write New Message		Delete Contact
	Unsent Message		Central Phonebook
	Sent Messages	1	

NOTE: Menu options are dependent upon system programming.

